

Here you can find the recent Bill of Materials for OVI40-SDR.

UI-PCB:

Please pay attention! This BOM is a preliminary and might change during betatest phase.

E.g.the SD-Cardreader which is listed here will be replaced in series because it is no longer available.

BOM OVI40-SDR UI V1.7		24-09-2017	DF80E	Distributor / Prices								
Part	Value	Description	Package	Amount	FARNELL	Price	Reichelt	Price	Mouser	Price	Digikey	Price
IC1 /IC12	WM8731	Audio CODEC WM8731	SSOP28	2					238-WM8731SEDS/V		WM8731SEDS/RVCT-ND	3,63
		or Audio CODEC TLV320AIC23BPWG4	SSOP28	2	120-7297	9,25						
IC2	LM4952TS	Ti Stereo Audio PA	LM4952	1	100-8028	3,72			926-LM4952TS/NOPB		LM4952TS/NOPB-ND	3,06
IC3	LP5907_Q1	Ti low noise LDO 3.3 Volt	SOT23-5	1	249-2304	0,654			595-LP5907QMF3-3.3Q1		296-38557-1-ND	0,47
IC4	STM32F76X_ZIT6	MCU	LQFP144	1	253-5499	12,84			511-STM32F767ZIT6		497-16521-ND	13,26
IC5	ASTX-H11	16 MHz TCXO 2,5ppm 3,2 x 2,5 mm	TCXO_32X25	1					815-ASTXH1116T		535-12044-1-ND	2,84
IC6	KA78RM33R	3.3 Volt LDO	DPAK	1	245-1041	0,681	TS 2940 CP33		821-TS2940CP33			
IC7	AT24CM02	I2C EEPROM	S008	1			24LC1026 JSN		579-24LC1026I/SN		AT24CM02-SSHM-B-ND	1,89
IC8	NCP5501DT50G	5.0 Volt LDO	DPAK	1	170-3369	0,602	TS 2940 CP50		821-TS2940CP50			
Q1	32,768 kHz	QCM-315_SMD	CM315	1					695-CM315D-32.7KEZFT		300-8813-1-ND	0,6
T3	BC857	PNP Transistor	SOT23	1	179-8067	0,02	BC 857C SMD	0,034	771-BC857CW115			
D5	BAV70	Double Diode	SOT23	2	267-7467	0,031	BAV 70 SMD	0,034	512-BAV70			
D6	BAV70	Double Diode	SOT23	.								
D7	BAS85	Schottky barrier diode	SOD80C	3	146-9394	0,23	BAS 85 SMD	0,034	771-BAS85135			
D8	BAS85	Schottky barrier diode	SOD80C	.								
D9	BAS85	Schottky barrier diode	SOD80C	.								
D1	green	LED	LED_3MM	1	276-4976	0,409	LED 3MM ST GN		710-151034GS03000			
D2	red	LED	LED_3MM	1	276-4977	0,361	LED 3MM ST RT		710-151034RS03000			
D3	blue	LED	LED_3MM	1	276-4975	0,443	LED 3MM ST BL		710-151034BS03000			
BAT1-HOLDER		Battery Holder CR2032		1	188-5903	2,98					BU2032-1-ND	0,66
BAT1	CR2032P_L	Lithium Battery 3,0Volt	CR_2032_H	1			CR 2032P-H					
X1	PN87520-S	USB Plug HOST	PN87520-S	1	117-7883	0,81	USB AW	0,2				
J11	MINI-USB_B	USB Plug DFU	MINI-USB_B	1	211-2367	0,561	USB BWM SMD	0,28				
LCD1	HY32D	3,2 Zoll LCD ILI9325	HY32D_UHSDR_MOD	1								
L1	47uH	L_SMD1005	L1005	3	221-5655	0,13			810-MLZ2012M470WT000		MLZ2012M470WT000	0,12
L2	47uH	L_SMD1005	L1005	.								
L3	47uH	L_SMD1005	L1005	.								
R1	47k	SMD Resistor TK50	0805	6			SMD-0805 47k	0,02	667-ERJ-U06F4702V			
R1A	100R	SMD Resistor TK50	0603	13			SMD-0603 100	0,03	667-ERJ-3RBD1000V			
R1B	0R	SMD Resistor TK50	0603	3			SMD-0603 0	0,03	667-ERJ-3GEY0R00V			
R2	1k	SMD Resistor TK50	0603	7			SMD-0603 1,0k	0,03	667-ERJ-S03F1001V			
R3	100R	SMD Resistor TK50	0603	.								
R4	1k	SMD Resistor TK50	0603	.								
R4B1	2R2	SMD Resistor TK50	1206	4			SMD 1/4W 2,2	0,03	71-CRCW12062R20FNEB			
R4D	2R2	SMD Resistor TK50	1206	.								
R5	0R	SMD Resistor TK50	0603	.								
R6	1k	SMD Resistor TK50	0603	.								
R7	1k	SMD Resistor TK50	0603	.								
R8	100R	SMD Resistor TK50	0603	.								
R9	4k7	SMD Resistor TK50	0805	4			SMD-0805 4,7k	0,02	667-ERJ-S06F4701V			
R10	4k7	SMD Resistor TK50	0603	1			SMD-0603 4,7k	0,02	667-ERJ-3EKF4701V			
R11	4k7	SMD Resistor TK50	0805	.								
R12	4k7	SMD Resistor TK50	0805	.								
R13	47R	SMD Resistor TK50	0603	7			SMD-0603 47	0,03	667-ERJ-3EKF47R0V			
R14	47R	SMD Resistor TK50	0603	.								
R15	1k	SMD Resistor TK50	0603	.								
R16	100R	SMD Resistor TK50	0603	.								
R17	100R	SMD Resistor TK50	0603	.								
R18	100R	SMD Resistor TK50	0603	.								
R19	100R	SMD Resistor TK50	0603	.								
R20	100R	SMD Resistor TK50	0603	.								
R21	47R	SMD Resistor TK50	0603	.								
R22	47R	SMD Resistor TK50	0603	.								
R23	0R	SMD Resistor TK50	0805	8			SMD-0805 0	0,02	667-ERJ-U060R00V			

Last update:
08.12.2017
12:25

en:projekte:ovi40-sdr:bom <https://amateurfunk-sulingen.de/wiki/doku.php?id=en:projekte:ovi40-sdr:bom&rev=1512735921>

R24	680R	SMD Resistor TK50	0805	4		SMD-0805 680	0,02	ERJ-6ENF6800V			
R25	4k7	SMD Resistor TK50	0805	.							
R26	100R	SMD Resistor TK50	0603	.							
R27	100R	SMD Resistor TK50	0603	.							
R28	100R	SMD Resistor TK50	0603	.							
R29	1k	SMD Resistor TK50	0603	.							
R30	0R	SMD Resistor TK50	0805	.							
R31	0R	SMD Resistor TK50	0805	.							
R32	0R	SMD Resistor TK50	0805	.							
R33	100R	SMD Resistor TK50	0603	.							
R34	100R	SMD Resistor TK50	0603	.							
R35A	4R7	SMD Resistor TK50	1206	1		SMD ¼W 4,7	0,03	71-CRCW12064R70FNEB			
R36	680R	SMD Resistor TK50	0805	.							
R37	680R	SMD Resistor TK50	0805	.							
R40	1k	SMD Resistor TK50	0603	.							
R41	47R	SMD Resistor TK50	0603	.							
R45	2R2	SMD Resistor TK50	1206	.							
R46	2R2	SMD Resistor TK50	1206	.							
R47	47R	SMD Resistor TK50	0603	.							
R48	47R	SMD Resistor TK50	0603	.							
R101	0R	SMD Resistor TK50	0603	.							
R108	0R	SMD Resistor TK50	0805	.							
R110	0R	SMD Resistor TK50	0805	.							
R112	0R	SMD Resistor TK50	0805	.							
R114	0R	SMD Resistor TK50	0805	.							
R116	680R	SMD Resistor TK50	0805	.							
R120	47k	SMD Resistor TK50	0805	.							
R121	47k	SMD Resistor TK50	0805	.							
R122	47k	SMD Resistor TK50	0805	.							
R123	47k	SMD Resistor TK50	0805	.							
R124	47k	SMD Resistor TK50	0805	.							
C1	1nF	SMD Chip Capacitor NP0/COG	0603	10		KEM COG0603 1,0N	0,01				
C1A	1nF	SMD Chip Capacitor NP0/COG	0603	.							
C1B	1nF	SMD Chip Capacitor NP0/COG	0603	.							
C1C	1nF	SMD Chip Capacitor NP0/COG	0603	.							
C1D	1nF	SMD Chip Capacitor NP0/COG	0603	.							
C2	1nF	SMD Chip Capacitor NP0/COG	0603	.							
C3	1nF	SMD Chip Capacitor NP0/COG	0603	.							
C4	1nF	SMD Chip Capacitor NP0/COG	0603	.							
C5	220uF	SMD Tantal-ELKO 10V	TA-C	5		TAJ 6032 220/10	0,46				
C6	220uF	SMD Tantal-ELKO 10V	TA-C	.							
C7	470nF	SMD Chip Capacitor NP0/COG	0603	4		NPO 0603 CD 470N	0,04				
C8	470nF	SMD Chip Capacitor NP0/COG	0603	.							
C9	220uF	SMD Alu-Elko 16V low ESR	E_SMD_0608	6		VF 220/16 P- D8	0,3				
C10	100nF	SMD Chip Capacitor X7R	0603	63		X7R 0603FCF 100N	0,04				
C11	100nF	SMD Chip Capacitor X7R	0603	.							
C12	10uF	SMD Tantal-ELKO 16V	TA-B 3,5 x 2,8	9		T494B 10U 16	0,51				
C13	10uF	SMD Tantal-ELKO 16V	TA-B 3,5 x 2,8	.							
C14	100nF	SMD Chip Capacitor X7R	0603	.							
C15	100nF	SMD Chip Capacitor X7R	0603	.							
C16	10uF	SMD Tantal-ELKO 16V	TA-B 3,5 x 2,8	.							
C17	10uF	SMD Tantal-ELKO 16V	TA-B 3,5 x 2,8	.							
C18	1uF	SMD Chip Capacitor NP0/COG	0603	8		NPO 0603 CE 1,0U	0,04				
C19	1uF	SMD Chip Capacitor NP0/COG	0603	.							
C20	470nF	SMD Chip Capacitor NP0/COG	0603	.							
C21	1nF	SMD Chip Capacitor NP0/COG	0603	.							
C22	10uF	SMD Tantal-ELKO 16V	TA-B 3,5 x 2,8	.							
C23	100nF	SMD Chip Capacitor X7R	0603	.							
C24	4.7uF	SMD Tantal-ELKO	TA-A 3,2 x 1,6	1		T491A 4,7U 16	0,04				
C25	100nF	SMD Chip Capacitor X7R	0603	.							
C26	100nF	SMD Chip Capacitor X7R	0603	.							

C27	220pF	SMD Chip Capacitor NPO/COG	0805	2			NPO 0805 BG 220P	0,04				
C28	220pF	SMD Chip Capacitor NPO/COG	0805	.								
C29	100nF	SMD Chip Capacitor X7R	0603	.								
C30	100nF	SMD Chip Capacitor X7R	0603	.								
C31	100nF	SMD Chip Capacitor X7R	0603	.								
C32	220uF	SMD Alu-Elko 16V low ESR	E_SMD_0608	.								
C32B	220uF	SMD Alu-Elko 16V low ESR	E_SMD_0608	.								
C33	220uF	SMD Alu-Elko 16V low ESR	E_SMD_0608	.								
C34	100nF	SMD Chip Capacitor X7R	0603	.								
C35	220uF	SMD Alu-Elko 16V low ESR	E_SMD_0608	.								
C36	1nF	SMD Chip Capacitor NPO/COG	0805	10			NPO G0805 1,0N	0,04				
C37	1nF	SMD Chip Capacitor NPO/COG	0805	.								
C38	1nF	SMD Chip Capacitor NPO/COG	0603	.								
C39	220uF	SMD Tantal-ELKO 10V	TA-C	.								
C40	470nF	SMD Chip Capacitor NPO/COG	0603	.								
C41	10uF	SMD Tantal-ELKO 16V	TA-B 3,5 x 2,8	.								
C42	100nF	SMD Chip Capacitor X7R	0603	.								
C43	100nF	SMD Chip Capacitor X7R	0603	.								
C44	100nF	SMD Chip Capacitor X7R	0603	.								
C45	100nF	SMD Chip Capacitor X7R	0603	.								
C46	100nF	SMD Chip Capacitor X7R	0603	.								
C47	100nF	SMD Chip Capacitor X7R	0603	.								
C48	100nF	SMD Chip Capacitor X7R	0603	.								
C49	100nF	SMD Chip Capacitor X7R	0603	.								
C50	100nF	SMD Chip Capacitor X7R	0603	.								
C51	100nF	SMD Chip Capacitor X7R	0603	.								
C52	100nF	SMD Chip Capacitor X7R	0603	.								
C53	100nF	SMD Chip Capacitor X7R	0603	.								
C54	100nF	SMD Chip Capacitor X7R	0603	.								
C55	100nF	SMD Chip Capacitor X7R	0603	.								
C56	100nF	SMD Chip Capacitor X7R	0603	.								
C57	100nF	SMD Chip Capacitor X7R	0603	.								
C58	100nF	SMD Chip Capacitor X7R	0603	.								
C59	100nF	SMD Chip Capacitor X7R	0603	.								
C60	100nF	SMD Chip Capacitor X7R	0603	.								
C61	100nF	SMD Chip Capacitor X7R	0603	.								
C62	100nF	SMD Chip Capacitor X7R	0603	.								
C63	100nF	SMD Chip Capacitor X7R	0603	.								
C64	100nF	SMD Chip Capacitor X7R	0603	.								
C65	100nF	SMD Chip Capacitor X7R	0603	.								
C66	100nF	SMD Chip Capacitor X7R	0603	.								
C67	1nF	SMD Chip Capacitor NPO/COG	0805	.								
C68	1nF	SMD Chip Capacitor NPO/COG	0805	.								
C69	1nF	SMD Chip Capacitor NPO/COG	0805	.								
C70	1nF	SMD Chip Capacitor NPO/COG	0805	.								
C71	1nF	SMD Chip Capacitor NPO/COG	0805	.								
C72	1nF	SMD Chip Capacitor NPO/COG	0805	.								
C73	1nF	SMD Chip Capacitor NPO/COG	0805	.								
C74	1nF	SMD Chip Capacitor NPO/COG	0805	.								

